



DATA SHEET DIESEL
GENERATOR SET







#### **►** Model

# GSBD22500S-UL

**ENGINE BRAND** 

BAUDOUIN


**ENGINE MODEL** 

12M55G5D2/6

ALTERNATOR BRAND > STAMFORD

GENERATOR CONTROLLER

**DSE 7310** 



# **▶** GENSET RATING

ENGINE	ALTERNATOR	VOLTAGE	PH	Hz	STANDBY POWER		POWER FACTOR	CURRENT
LINGINE	ALIERNATOR	V		112	kW KVA			Α
	P80LVSI804S	480/277	3	60	2500	3125	0.8	3763
12M55G5D2/6	P80LVSI804W	600/346	3	60	2500	3125	0.8	3010

# Certifications







# **► ENGINE FEATURES**

>>	BRAND	▶ BAUDOUIN
>>	MODEL	▶ 12M55G5D2/6
>>	EXHAUST EMISSIONS	▶ TIER 2
>>	RPM	▶ 1800
>>	STANDBY RATING kwm	▶ 2700
>>	STANDBY RATING bhp	▶ 3621
>>	PRIME RATING kwm	▶ 2450
>>	PRIME RATING bhp	<b>3286</b>
>>	NUMBER OF CYLINDERS	▶ 12
>>	ASPIRATION	► TURBOCHARGED AND AFTERCOOLED
>>	DISPLACEMENT in3	▶ 4006
>>	ENGINE AIR FLOW CFM (m3/min)	▶ 6967
<b>&gt;&gt;</b>	GOVERNOR TYPE	▶ ELECTRONIC
>>	CONTROL VOLTAGE v	▶ 24
>>	BORE/STROKE, in	▶ 7.08X8.46(180X215)
>>	COOLANT CAPACITY WITHOUT RADIATOR gal	▶ 80.83
>>	OIL CAPACITY, TOTAL gal	▶ 121.51

# **▶ FUEL CONSUMPTION**


	STANDBY POWER	
LOAD	GAL/hr	L/hr
100%	174.69	661.3
75%	118.79	449.7
50%	87.62	331.7
25%	48.52	183.7

# **► ALTERNATOR FEATURES**

>>	BRAND	■ STAMFORD
>>	MODEL	▶ P80LVSI804S / P80LVSI804W
>>	FREQUENCY	▶ 60 Hz
>>	PHASES	▶ 3
>>	WINDING LEADS	▶ 12
>>	INSULATION SYSTEM	▶ H CLASS
>>	CONTROL SYSTEM	SEPARATELY EXCITED BY P.M.G.
>>	PROTECTION	▶ IP23
>>	POWER FACTOR	▶ 0.8
>>	COOLING AIR CFM	•
>>	VOLTAGE REGULATION (%)	<b></b> ▶ +-0.5



#### **▶** GENERATOR CONTROLLER



# » MODEL **DEEP SEA 7310**

The DSE7310 MKII is an Auto Start Control Module and the DSE7320MKII is an Auto Mains (Utility) Failure Control Module suitable for a wide variety of single, diesel or gas, gen-set applications.

Monitoring an extensive number of engine parameters, the modules will display warnings, shutdown and engine status information on the back-lit LCD screen, illuminated LEDs, remote PC and via SMS text alerts (with external modem). The DSE7320 MKII will also monitor the mains (utility) supply. The modules include USB, RS232 and RS485 ports as well as dedicated DSENet® terminals for system expansion.

#### **KEY FEATURES**

- 4-Line back-lit LCD text display
- Multiple Display Languages
- Five key menu navigation
- LCD alarm indication
- · DSENet expansion compatibility
- Internal PLC editor
- Protections disable feature
- Fully configurable via PC using USB, RS232 & RS485 communication
- Front panel configuration with PIN protection
- Power save mode
- 3 phase generator sensing and protection
- 3 phase mains (utility) sensing and protection (DSE7320 MKII only)
- Automatic load transfer control (DSE7320 MKII only)
- · Generator current and power monitoring (kW, kvar, kVA, pf)
- · Mains current and power monitoring (kW, kvar, kVA, pf) (DSE7320 MKII only)
- · kW and kvar overload and reverse power alarms

- · Over current protection
- Unbalanced load protection
- Independent earth fault protection
- · Breaker control via fascia buttons
- Fuel and start outputs configurable when using CAN
- 6 configurable DC outputs
- 2 configurable volt-free relay outputs
- 6 configurable analogue/digital inputs
- Support for 0 V to 10 V & 4 mA to 20 mA sensors
- 8 configurable digital inputs
- Configurable 5 stage dummy load and load shedding outputs
- CAN, MPU and alternator frequency speed sensing in one variant
- · Real time clock
- Manual and automatic fuel pump control
- Engine pre-heat and post-heat functions
- · Engine run-time scheduler
- Engine idle control for starting & stopping • Fuel usage monitor and low fuel level alarms
- Simultaneous use of RS232 and RS485 communication ports
- True dual mutual standby using RS232 or RS485 for accurate engine hours balancing.
- MODBUS RTU support with configurable MODBUS pages.
- Advanced SMS messaging (additional external modem required)
- Start & stop capability via SMS messaging
- 3 configurable maintenance alarms
- · Compatible with a wide range of CAN engines, including tier 4 engine support


- · Uses DSE Configuration Suite PC Software for simplified configuration
- Licence-free PC software
- IP65 rating (with supplied gasket) offers increased resistance to water ingress
- · Modules can be integrated into building management systems (BMS) using MODBUS RTU

#### **KEY BENEFITS**

- Automatically transfers between mains (utility) and generator (DSE7320 MKII only) for convenience.
- Hours counter provides accurate information for monitoring and maintenance periods
- User-friendly set-up and button layout for ease of use
- Multiple parameters are monitored & displayed simultaneously for full visibility
- The module can be configured to suit a wide range of applications for user flexibility
- PLC editor allows user configurable functions to meet user specific application requirements.



#### ▶ DIMENSIONS AND WEIGHT



# ► ACOUSTIC ENCLOSURE

Acoustic enclosure designed and manufactured with 14 gauge carbon steel sheet, polyurethane acoustic coating, access and air expulsion to avoid gas accumulation, drainage system to avoid liquid accumulation. Electrostatic painting for extended life.

We have options for enclosures in aluminum or stainless steel

## ► STANDARD FEATURES & ACCESSORIES

$\Theta$	DSE 9470 Battery Charger
$\bigcirc$	Battery and Battery Rack
$\Theta$	ABB Main Line Circuit Breaker
$\bigcirc$	AVR
$\Theta$	Hotstart Pre heater 2 RMP-CSM10902-000
$\Theta$	Residential Grade Silencer Open Unit
$\bigcirc$	Critical Grade Silencer Inside Enclosure

$\bigcirc$	Emergency Stop Button
$\bigcirc$	Flex Fuel Lines
$\bigcirc$	Protection Covers for Rotating Parts
$\bigcirc$	Exhaust Insulation Cover
$\bigcirc$	Anti Vibration Pads between Engine/Alternator & Base Frame
$\bigcirc$	Operation and Maintenance manuals
$\bigcirc$	24 Months /1000 hours Limited Standby Warranty



# **▶ OPTIONAL ACCESSORIES**

Paralleling Adder (DSE8610 & Motorized Breaker)		Enclosure AC light and On/Off Switch
120V GFCI Receptacle		Enclosure DC light and On/Off Switch
240V Receptacle		Enclosure space Heater (1500w/120v)
Alternator Strip Heater		Load Center / Distribution Board (100 A, 12 Breaker)
Battery Blanket Heater		Load Center / Distribution Board (200 A, 8 Breaker)
Battery Disconnect Switch		AVR UPGRADE
Battery Pad Heater		Oil Pan Heater
Battery Restraint		Relay - 10A Common Alarm
Control Panel Heater		Relay - 10A Run Relay
DSE2157 Output Module (8 dry contacts)	e e e e e e e e e e e e e e e e e e e	Remote E-Stop- Breaker Glass Type / Nema 3R
DSE2520 Remote Display Module		Remote E-Stop- Breaker Glass Type / Nema 4X
DSE2548 Remote Annunciator (16 light)	0	Remote E-Stop- Flush Mount
DSE2548 Remote Annunciator (24 light)		Remote E-Stop- Surface Mount
DSE2548 Remote Annunciator (8 light)		Remote E-Stop- Visual/ Plastic Hinged Cover
DSE890 3G GATEWAY		Spring Isolator- Non Seismic (ACE 121 Series) SKIRT NOT INCLUDED
GSM/GPS ANTENNA 3M RG-174, GSM-SMA(M), GPS-SMA(F)		Spring Isolator- Seismic/Restraint (ACE 821 Series) SKIRT NOT INCLUDE
DSE9641 10A Battery Charger		Voltage Adjust Rheostat
DSE9470 10A Battery Charger		Automatic Transfer Switch

# **▶ OPTIONAL UL142 SUB BASE TANK**

	24 hr	48 hr	72 hr
Fuel Capacily (gal)	4700		
Dimensions (L/W/H) in			
Weight lb			





IGSA CORP. 5918 Santa Ave Laredo, Texas 78041 Tel. +1 956.7914.472



Model: **12M55G5D2/6** Date: 30/11/22

# **PowerKit Engine Datasheet**

Page: 1/4

#### Ratings

	Gross Engine Output				Net Engine Output			
RPM	PF	RP	ES	SP	PF	RP	ES	SP
	kWm	ВНР	kWm	ВНР	kWm	ВНР	kWm	ВНР
1800	2450 *	3286 *	2700	3621	\*	\*	\	\

1 kWm = 1,34102 BHP

When the engine is used with a cooling system using an electrically driven fan, net engine output data may change and quoted figures should be used for reference only

#### **Basic data**

Engine model		12M55G5D2/6
N° of Cylinders / Valves		12 / 48
Cylinders arrangement		At Vee
Bore x Stroke (mm)		180 x 215
Displacement (L)		65.65
Thermodynamic Cycle		Diesel 4 stroke
Firing Order	A1-B1-A5-	B5-A3-B3-A6-B6-A2-B2-A4-B4
Mean Piston Speed (m/s)		12.9
BMEP @ ESP (Bar)		27.42
Cooling System		Liquid (water + 50% antifreeze)
Injection System		Direct
Fuel System		High Pressure Common Rail
Aspiration		Turbocharged and Aftercooled
Compression ratio		16.5 : 1
Flywheel housing		SAE 00
Flywheel		21"
Rotation Viewed from Flywhe	el	Counterclockwise
Allowed static bending mome	nt of the flywheel housing	/
N° of teeth on flywheel ring ge	ear	202
Inertia of flywheel (kg•m²)		20.78
Inertia of crankshaft (kg•m²)		16.16
Emission standard		EPA Tier2
Overall Dimensions without ra	adiator (Length x Width x Height) (mm)	2958 × 1544 ×2616
Engine dry weight without rad	iator and without radiator pipes (kg)	9550
Engine dry weight with radiate	or and radiator pipes (kg)	N/A
Engine wet weight with radiate	or (includes oil, coolant) (kg)	N/A

★ The indicated PRP Power is for reference only. This engine is designed for emergency standby power (ESP) applications only.



Model: **12M55G5D2/6** Date: 30/11/22

Page:

2/4

# **PowerKit Engine Datasheet**

Air intake system Air intake temperature rise (°C) .....≤ 5 Air intake restriction clean filter (mBar) .....≤ 30 Air intake restriction dirty filter (mBar) .....≤ 70 Recommended air flow @ PRP (m³/min) ......193.9 Recommended air flow @ ESP (m³/min) ......197.3 Aftercooling system ......Air to Water Aftercooler system type Max. difference between intake temperature and ambient temperature (°C) ......30 Max. intake pressure drop of aftercooler (mBar) ......50 Lubrication system Oil capacity Low / High (L) Oil pressure in normal condition idle speed (Bar) .....≥ 1.8 Lowest oil pressure alarm (shutdown) (Bar) ......1.8 High Oil Pressure Warning Max. oil temperature (°C) Oil fuel consumption ratio based on engine fuel consumption data .....≤ 0.4g/kW·h Heat balance test data (with ambient temperature 25 °C) Heat Rejection to Jacket Water @ ESP (kJ/s) ......1055 Heat Rejection to Low temperature circuit @ ESP (kJ/s) ......609 Radiated Heat to Ambient @ ESP (kJ/s) ......91 Heat Rejected to Exhaust @ ESP (kJ/s) ......2127 **Exhaust system** Max. exhaust temperature before turbocharger (°C) .......740 Max. exhaust temperature after turbocharger (°C) ......550 Exhaust flow @ ESP (m³/min) .......642.7 Min. diameter of exhaust pipe (mm) .......280 Max. bending moment of exhaust gas exit flange (Nm) ......10



Model: 12M55G5D2/6 Date: 30/11/22 **PowerKit Engine Datasheet** Page: 3/4

#### Cooling system without radiator

Cooling system without ra	adiator			
System designed for ambient	temperature up to (°C) <sup>1</sup>	\		
Radiator type		\		
Fan type		\		
Min. inside diameter of coolan-	t outlet pipe (mm)	LT 76 / HT 96		
	nd pipes (L)			
Coolant alarm (shutdown) tem	perature (°C)	112		
Thermostat opening temperatu	ure / full open temperature (°C)	80 / 92		
Max. additional restriction for e	external cooling circuit (Bar)	HT 0.6 / LT 0.4		
Coolant capacity of the engine	· (L)	306		
_				
Fan absorbed power (kW)		\		
Additional restriction (for refere	ence) - Duct allowance (Pa)	150		
* Air flow figure assumes the presence of	the standard radiator provided, taking into consideration the backpr	ressure caused		
Fuel system				
Governor		ECU		
Governor steady state speed s	stability at constant load (ISO 8528-5 Class G3) $^{\mathrm{2}}$	≤ +/- 0.5 %		
Max. restriction at fuel inlet (Ba	ar)	0.1		
Max. pressure at fuel inlet (Ba	r)	0.5		
Max. fuel return restriction (Ba	r)	0.2		
Max. fuel inlet temperature (°C	c)	50		
Fuel supply flow (L/hr)		2800		
Min. internal diameter of inlet p	pipe (mm)	19		
Min. internal diameter of return	n pipe (mm)	19		
Electrical system				
Electrical system voltage (neg	ative to ground) (Vdc)	24		
Starter power (kW)		2 x 10		
Battery charger current (A)		55		
Battery charger absorbed pow	er (kW)	1.6		
Max. electric resistance of star	ting circuit (Ω)	0.008		
Min. sectional area of wire (mm²)				
Min. cold start temperature wit	hout auxiliary starting device (°C) 3	10		
Min. cold start temperature wit	h auxiliary starting device (°C) <sup>3</sup>	TBD		

The indicated value is based on the AOT value of \°C for an engine tested at 100% of the ESP Power, reflecting temperature in an open condition, without an enclosure or container, without any airflow obstruction in the front of the radiator, without air recirculation, with free exhaust gas exit and with the engine thermostatic valve in its full open condition, without a closing plate present. The reference air restriction is equal to 50Pa. For the equivalent ATB (Air-to-Boil) performance in a customer or project basis, please consult Baudouin Application Engineering.

DPK-TDS-EN-12M55-9004-22-11-30 Moteurs Baudouin reserve the right to modify these specifications, without notice. Document not contractual

This refers only to the frequency response of the engine and should not be confused with the performance class of the Generator Set, which is subject to additional contributing factors such as alternator selection and control settings.

Engines used in emergency standby application or applications that require immediate start under load, they must be equipped with coolant heaters. Baudouin recommend heaters installation to be executed by providing constant coolant circulation across all the engine components. Two heaters are required for V-type engines, one per each side.

Model: 12M55G5D2/6 Date: 30/11/22

Page:

4/4

# PowerKit Engine Datasheet

#### **Noise**

Diesel engine noise (Acoustic power level) (dB(A))	124.8
Noise - upper side (dB(A))	107.6
Noise - right side (view from flywheel) (dB(A))	106.8
Noise - left side (view from flywheel) (dB(A))	107.5
Noise – front (radiator) side (dB(A))	107.5
Noise – rear (flywheel) side (dB(A))	106.8
Notes:	

- a) Noise test made at 100% of the ESP power, at 1 mt. distance, on engine without radiator, without cooling fan and without silencer.
- b) Noise test refers to ISO 6798 norm: "Reciprocating internal combustion engines. Measurement of emitted airborne noise. Engineering method and survey method".

#### **Fuel consumption**

Rating	gr/kWh	L/hr	
100% ESP	205.9	661.3	
100% PRP	208.0 606.8		
75% PRP	218.5	449.7	
50% PRP	227.5	331.7	
25% PRP	251.9	183.7	
	Fuel consumption	tolerance +/- 5%	

#### Notes:

This engine is designed for ESP (Emergency Standby) applications only, the values shown above at PRP levels refer to the Referenced Power ( 2450 kWm).

#### **Ratings definitions**

#### **Emergency Standby Power (ESP)**

Emergency Standby Power is the maximum power available for a varying load for the duration of a main power network failure. The average load factor over 24 hours of operation should not exceed 70% of the engine's ESP power rating. Typical operational hours of the engine is 200 hours per year, with a maximum usage of 500 hours per year. This includes an annual maximum of 25 hours per year at the ESP power rating. No overload capability is allowed. The engine is not to be used for sustained utility paralleling applications.


#### **Prime Power (PRP)**

Prime Power is the maximum power available for unlimited hours of usage in a variable load application. The average load factor should not exceed 70% of the engine's PRP power rating during any 24 hour period. An overload capability of 10% is available, however, this is limited to 1 hour within every 12 hour period.

- 1) All ratings are based on operating conditions under ISO 8528-1, ISO 3046, DIN6271. Performance tolerance of ±5%.
- 2) Test conditions: 100 kPa, 25°C air inlet temperature, relative humidity of 30%, with fuel density 0.84 kg/L. Derating may be required for conditions outside these; please contact the factory for details.
- 3) Power output curves are based on the engine operating with fuel system, water pump and lubricating oil pump; not included are battery charging alternator, fan and optional equipment.

# STAMFORD AVK

#### LV 804 W WDG 07 - Technical Data Sheet



#### FRAME LV 804 W

#### STAMFORD | AvK

#### SPECIFICATIONS & OPTIONS

#### **STANDARDS**

Cummins Generator Technologies industrial generators meet the requirements of BS EN 60034 and the relevant sections of other national and international standards such as BS5000, VDE 0530, NEMA MG1-32, IEC60034, CSA C22.2-100, AS1359.

Other standards and certifications can be considered on request.

#### **DESCRIPTION**

The STAMFORD PI range of synchronous ac generators are brushless with a rotating field. They are separately excited by the STAMFORD Permanent Magnet Generator (PMG). This is a shaft mounted, high frequency, pilot exciter which provides a constant supply of clean power via the Automatic Voltage Regulator (AVR) to the main exciter. The main exciter output is fed to the main rotor, through a full wave bridge rectifier, protected by surge suppression.

#### **VOLTAGE REGULATORS**

The P80 range generators complete with a PMG are available with one AVR. Underspeed protection (UFRO) is also provided by the AVR. The UFRO will reduce the generator output voltage proportional to the speed of the generator below a pre-settable level.

The STAMFORD | AvK Digital Excitation Control System (DM110) is an electronic, solid-state, microprocessor based control device. The DM110 regulates the output voltage of a the ac generator by controlling the current into the generator exciter field. Input power to the DM110 is provided by a multi-pole, high-frequency, permanent magnet generator (PMG).

The DM110 is supplied in an encapsulated package designed for behind-the-panel mounting. Front panel indicators (LEDs) annunciate DM110 status and system conditions. DM110 connections are made through quarterinch, quick-connect terminals on the rear panel. A 9-pin DB-9 type connector on the rear panel provides communication between the DM110 and an IBM compatible PC.

Technical details on the DM110 are available on the Stamford-AvK website using the following URL: <a href="https://www.stamford-avk.com/downloads/avr-manuals">https://www.stamford-avk.com/downloads/avr-manuals</a>

#### **WINDINGS & ELECTRICAL PERFORMANCE**

All generator stators are wound to 2/3 pitch. This eliminates triplen (3rd, 9th, 15th ...) harmonics on the voltage waveform and is found to be the optimum design for trouble-free supply of non-linear loads. The 2/3 pitch design avoids excessive neutral currents sometimes seen with higher winding pitches. A fully connected damper winding reduces oscillations during paralleling. This winding, with the 2/3 pitch and carefully selected pole and tooth designs, ensures very low levels of voltage waveform distortion.

#### **TERMINALS & TERMINAL BOX**

Standard generators feature a main stator with 6 ends brought out to the terminals, which are mounted on the frame at the non-drive end of the generator. A sheet steel terminal box contains the AVR and provides ample space for the customers' wiring and gland arrangements. It has removable panels for easy access.

#### **SHAFT & KEYS**

All generator rotors are dynamically balanced to better than BS6861:Part 1 Grade 2.5 for minimum vibration in operation. Two bearing generators are balanced with a half key.

#### INSULATION/IMPREGNATION

The insulation system is class 'H'.

All wound components are impregnated with materials and processes designed specifically to provide the high build required for static windings and the high mechanical strength required for rotating components.

#### **QUALITY ASSURANCE**

Generators are manufactured using production procedures having a quality assurance level to BS EN ISO 9001.

#### **NOTE ON REGULATION**

The stated voltage regulation may not be maintained in the presence of certain radio transmitted signals. Any change in performance will fall within the limits of Criteria 'B' of EN 61000-6-2:2001. At no time will the steady-state voltage regulation exceed 2%.

NB Continuous development of our products entitles us to change specification details without notice, therefore they must not be regarded as binding.

Front cover drawing is typical of the product range.

#### STAMFORD AVK


# FRAME LV 804 W WINDING 07

RATINGS	REFER TO SALES AND SERVICE BRIEFING	
MAXIMUM ALTITUDE	1000 METRES ABOVE SEA LEVEL	
MAXIMUM AMBIENT TEMPERATURE	40° C	
CONTROL SYSTEM SERIES 3	SEPARATELY EXCITED BY P.M.G.	
A.V.R.	FULL WAVE RECTIFIED	
VOLTAGE REGULATION	± 0.25%	
SUSTAINED SHORT CIRCUIT	REFER TO SHORT CIRCUIT DECREMENT CURVES OF THIS SECTION	
3031AINED SHORT CIRCOIT	THE ENTROSHORT GIRCOIT BEGILINERT CONVES OF THIS SECTION	
INSULATION SYSTEM	CLASS H	
PROTECTION	IP23 STANDARD	
RATED POWER FACTOR	0.8	
STATOR WINDING	DOUBLE LAYER LAP	
WINDING PITCH	2/3	
WINDING LEADS	6	
R.F.I. SUPPRESSION	BS EN 50081/2-1/2 VDE 0875G VDE 0875N For other standards apply to the factory	
WAVEFORM DISTORTION	NO LOAD < 1.5% NON-DISTORTING BALANCED LINEAR LOAD < 3.0%	
MAXIMUM OVERSPEED	2250 Rev/Min	
BEARING DRIVE END	ISO 6236 C3	
BEARING NON DRIVE END	ISO 6324 C3	
EFFICIENCY	REFER TO EFFICIENCY CURVES OF THIS SECTION	
FREQUENCY	60Hz	
TELEPHONE INTERFERENCE	TIF< 50	
COOLING AIR	4.5 m <sup>3</sup> /sec	
VOLTAGE STAR (Y)	600	
kVA BASE RATING FOR		
REACTANCE VALUES	4142	
Xd DIRECT AXIS SYNCHRONOUS	2.300	
X'd DIRECT AXIS TRANSIENT	0.167	
X"d DIRECT AXIS SUB-TRANSIENT	0.122	
Xq QUADRATURE AXIS REACTANCE	1.600	
X"g QUAD. AXIS SUB-TRANSIENT	0.228	
XLLEAKAGE REACTANCE	0.070	
X2 NEGATIVE PHASE SEQUENCE	0.175	
X <sub>0</sub> ZERO PHASE SEQUENCE	0.024	
REACTANCES ARE SATURATED	VALUES ARE PER UNIT AT RATING AND VOLTAGE INDICATED	
T'd TRANSIENT TIME CONSTANT	0.209	
T"d SUB-TRANSIENT TIME CONSTANT	0.016	
T'do O.C. FIELD TIME CONSTANT	5.060	
Ta ARMATURE TIME CONSTANT	0.077	
SHORT CIRCUIT RATIO	1/Xd	
STATOR WINDING RESISTANCE (LAN)	0.000470	
STATOR WINDING RESISTANCE (L-N) ROTOR WINDING RESISTANCE	0.000479 1.470	
EXCITER STATOR FIELD RESISTANCE		
	17.00	
EXCITER ROTOR RESISTANCE (L-L)	0.092	
PMG STATOR RESISTANCE (L-L)	3.800  RESISTANCE VALUES ARE IN OHMS AT 20° C	
	NESISTAINUE VALUES ARE IN UMMS AT ZUE C	
NO LOAD EXCITATION VOLTAGE	15.0	
FULL LOAD EXCITAION VOLTAGE	67.0	


Continuous development of our products entitles us to change specification details without notice, therefore they must not be regarded as binding.

## FRAME LV 804 W WDG 07

#### THREE PHASE EFFICIENCY CURVES




# FULL WAVE RECTIFIED AVR LOCKED ROTOR MOTOR STARTING CURVE



#### FRAME LV 804 W WDG 07 60Hz

Three Phase Short Circuit Decrement Curve No- Load Excitation at Rated Speed

Based on series star (wye) connection



#### OTE 1

THE FOLLOWING MULTIPLICATION FACTORS SHOULD BE USED TO ADJUST THE VALUES FROM CURVES BETWEEN THE 0.001 SECONDS AND THE MINIMUM CURRENT POINT IN RESPECT OF NOMINAL OPERATING VOLTAGE

VOLTAGE FACTOR X 1.00

THE SUSTAINED CURRENT VALUE IS CONSTANT IRRESPECTIVE OF VOLTAGE LEVEL

NOTE 2

THE FOLLOWING MULTIPLICATION FACTORS SHOULD BE USED TO CONVERT THE VALUES CALCULATED IN ACCORDANCE WITH NOTE 1 TO THOSE APPLICABLE

TO THE VARIOUS TYPES OF SHORT CIRCUIT

	3 PHASE	2 PHASE L-L	1 PHASE L-N
INSTANTANEOUS	X 1.0	X 0.87	X 1.30
MINIMUM	X 1.0	X 1.80	X 3.20
SUSTAINED	X 1.0	X 1.50	X 2.50
MAX SUSTAINED DURATION	10 SEC	5 SEC	2 SEC
ALL OTHER TIMES ARE LINCHANGED			

SUSTAINED SHORT CIRCUIT = 18334 Amps

#### FRAME LV 804 W


#### STAMFORD AVK

#### WINDING 07 0.8 Power Factor


#### **RATINGS**

Class - Temp Rise	Cont. F - 105/40 ℃	Cont. H - 125/40 ℃	Standby - 150/40 ℃	Standby - 163/27℃
<b>50</b> Hz Star (V)	N/A	N/A	N/A	N/A
kVA	N/A	N/A	N/A	N/A
kW	N/A	N/A	N/A	N/A
Efficiency (%)	N/A	N/A	N/A	N/A
kW Input	N/A	N/A	N/A	N/A
<b>60</b> Hz Star (V)	600	600	600	600
kVA	3871	4142	4430	4550
kW	3097	3314	3544	3640
Efficiency (%)	96.4	96.3	96.3	96.3
kW Input	3214	3439	3681	3781


#### TYPICAL DIMENSIONS - Further arrangements available - please refer to factory











#### STAMFORD AvK











Certificate Number UL-US-2345744-0 Report Reference AU6440-20231107

Date 10-Nov-2023

IGSASADECV Issued to:

PROLONGACION PASEO DE LA REFORMA # 2977

COL CUAJIMALPA MEXICO, Mexico 05000

Mexico

This is to certify that representative samples of FTSR - Engine Generators

See Addendum Page for Product Designation(s).

Have been evaluated by UL in accordance with the

Standard(s) indicated on this Certificate.

UL 2200, 2nd Ed., Issue Date: 2012-06-01, Revision Date: Standard(s) for Safety:

2015-07-29

Additional Information: See the UL Online Certifications Directory at

https://ig.ulprospector.com for additional information

This Certificate of Compliance indicates that representative samples of the product described in the certification report have met the requirements for UL certification. It does not provide authorization to apply the UL Mark. Only the Authorization Page that references the Follow-Up Services Procedure for ongoing surveillance provides authorization to apply the UL Mark.

Only those products bearing the UL Mark should be considered as being UL Certified and covered under UL's Follow-Up Services.

Look for the UL Certification Mark on the product.

Deborah Jennings-Conner, VP Regulatory Services d documentation involving UL Mark services are provided on behalf of UL LLC (UL) or any authorized licensee of UL. For questions, plo



Certificate Number UL-US-2345744-0

Report Reference AU6440-20231107

Date 10-Nov-2023

This is to certify that representative samples of the product as specified on this certificate were tested according to the current UL requirements

Model	Category Description	
GSBD00700S, GSBD00700L, GSBD00700LT GSBD00700W	Engine Generators	
GSBD00800S, GSBD00800L, GSBD00800LT GSBD00800W	Engine Generators	
GSBD01000S, GSBD01000L, GSBD01000W	Engine Generators	
GSBD01300S, GSBD01300L, GSBD01300W	Engine Generators	
GSBD01500S, GSBD01500L, GSBD01500W	Engine Generators	
GSBD01700S, GSBD01700L, GSBD01700W, GSBD01750S, GSBD01750L	Engine Generators	
GSBD01800S, GSBD01800L	Engine Generators	
GSBD02000S, GSBD02000L	Engine Generators	
GSBD02300S, GSBD02300L	Engine Generators	
GSBD02500S, GSBD02500L	Engine Generators	
GSBD02640S, GSBD02640L	Engine Generators	
GSBD02800S, GSBD02800L	Engine Generators	
GSBD03000S, GSBD03000L	Engine Generators	
GSBD03300S, GSBD03300L	Engine Generators	
GSBD30600S, GSBD30600L, GSBD30600LT GSBD30600W	Engine Generators	
GSBD30633S, GSBD30633L, GSBD30633LT GSBD30633W	Engine Generators	
GSBD30644S, GSBD30644L, GSBD30644LT GSBD30644W	Engine Generators	

Debrah Jenning - Course

Deborah Jennings-Conner, VP Regulatory Services

UL LLC



Certificate Number UL-CA-2339551-0
Report Reference AU6440-20231107

Date 10-Nov-2023

Issued to: IGSA S A DE C V

PROLONGACION PASEO DE LA REFORMA # 2977

COL CUAJIMALPA MEXICO, Mexico 05000

Mexico

This is to certify that representative samples of

FTSR7 - Engine Generators Certified for Canada See Addendum Page for Product Designation(s).

Have been evaluated by UL in accordance with the

Standard(s) indicated on this Certificate.

Standard(s) for Safety: CSA C22.2 No. 14, Edition 13, Issue Date 2018-03,

Revision Date 2022-06

Additional Information: See the UL Online Certifications Directory at

https://ig.ulprospector.com for additional information

This Certificate of Compliance indicates that representative samples of the product described in the certification report have met the requirements for UL certification. It does not provide authorization to apply the UL Mark. Only the Authorization Page that references the Follow-Up Services Procedure for ongoing surveillance provides authorization to apply the UL Mark.

Only those products bearing the UL Mark should be considered as being UL Certified and covered under UL's Follow-Up Services.

Look for the UL Certification Mark on the product.

Deborah Jennings-Conner, VP Regulatory Services

UL LLC



Certificate Number UL-CA-2339551-0

Report Reference AU6440-20231107

Date 10-Nov-2023

This is to certify that representative samples of the product as specified on this certificate were tested according to the current UL requirements

Model	Category Description	
GSBD00700S, GSBD00700L, GSBD00700LT GSBD00700W	Engine Generators	
GSBD00800S, GSBD00800L, GSBD00800LT GSBD00800W	Engine Generators	
GSBD01000S, GSBD01000L, GSBD01000W	Engine Generators	
GSBD01300S, GSBD01300L, GSBD01300W	Engine Generators	
GSBD01500S, GSBD01500L, GSBD01500W	Engine Generators	
GSBD01700S, GSBD01700L, GSBD01700W, GSBD01750S, GSBD01750L	Engine Generators	
GSBD01800S, GSBD01800L	Engine Generators	
GSBD02000S, GSBD02000L	Engine Generators	
GSBD02300S, GSBD02300L	Engine Generators	
GSBD02500S, GSBD02500L	Engine Generators	
GSBD02640S, GSBD02640L	Engine Generators	
GSBD02800S, GSBD02800L	Engine Generators	
GSBD03000S, GSBD03000L	Engine Generators	
GSBD03300S, GSBD03300L	Engine Generators	
GSBD30600S, GSBD30600L, GSBD30600LT GSBD30600W	Engine Generators	
GSBD30633S, GSBD30633L, GSBD30633LT GSBD30633W	Engine Generators	
GSBD30644S, GSBD30644L, GSBD30644LT GSBD30644W	Engine Generators	

Debrah Jenning - Course

Deborah Jennings-Conner, VP Regulatory Services

UL LLC



Certificate Number MH63698

Report Reference MH63698-20200103 Issue Date 2020-JANUARY-08

Issued to: IGSA S A DE C V

PROLONGACION PASEO DE LA REFORMA 2977

COL CUAJIMALPA 05000 MEXICO DF MEXICO

This certificate confirms that

SPECIAL-PURPOSE TANKS

representative samples of Secondary Containment Generator Base Tanks

Have been investigated by UL in accordance with the

Standard(s) indicated on this Certificate.

Standard(s) for Safety: UL 142, STANDARD FOR STEEL ABOVEGROUND

TANKS FOR FLAMMABLE AND COMBUSTIBLE LIQUIDS.

UL 142A STANDARD FOR SPECIAL PURPOSE

ABOVEGROUND TANKS FOR SPECIFIC FLAMMABLE

OR COMBUSTIBLE LIQUIDS.

CAN/ULC S601, STANDARD FOR SHOP FABRICATED STEEL ABOVEGROUND TANKS FOR FLAMMABLE AND

COMBUSTIBLE LIQUIDS.

Additional Information: See the UL Online Certifications Directory at

https://iq.ulprospector.com for additional information.

This *Certificate of Compliance* does not provide authorization to apply the UL Mark. Only the UL Follow-Up Services Procedure provides authorization to apply the UL Mark.

Only those products bearing the UL Mark should be considered as being UL Certified and covered under UL's Follow-Up Services.

Look for the UL Certification Mark on the product.

Ba Wally

Bruce Mahrenholz Director North

Bruce Mahrenholz, Director North American Certification Program

UL LLC

Any information and documentation involving UL Mark services are provided on behalf of UL LLC (UL) or any authorized licensee of UL. For questions, please contact a local UL Customer Service Representative at <a href="http://ul.com/aboutul/locations/">http://ul.com/aboutul/locations/</a>

